



EBT5X Portable Powerbank Capacity: 5200 mAh

User Manual



© 2012 Kinivo LLC. All rights reserved.

Kinivo is a trademark of Kinivo LLC. Bluetooth word mark and the Bluetooth logo are registered trademarks of Bluetooth SIG. All other trade names are registered trademarks of respective manufacturers. This manual may not be copied in any media or form without the written consent of Kinivo LLC.

Kinivo Product Support

Online : <http://support.kinivo.com>

Email : support@kinivo.com

Table of Contents

● Introduction	3
● Contents.....	3
● MFB Button Operation.....	3
● Technical Specification	4
● Compatibility.....	4
● Android Devices	5
● Charging your device.....	5
● Charging EBT5X.....	6
● Checking battery status	6
● Safety Notice	7
● Troubleshooting.....	7
● Warranty	8
● Online Support / Contact Us.....	9

Introduction

The EBT5X is a portable battery backup that can be carried anywhere to provide power to smartphones, tablets, PDAs and other USB powered devices. It has a built-in torch that can be used as SOS as well as for lighting. The remaining battery capacity can be checked using the LED indicators.

Contents

- 5200 mAh capacity power bank
- Micro USB cable
- Carrying Pouch

MFB Button Operation



- The first press of the MFB button shows the battery status by LED indicators and also wakes up the battery of EBT5X
- The second press of the MFB button turns on the SOS (LED Torch)
- The third press of the MFB button turns on the LED Torch
- The fourth press of the MFB button turns OFF the LED Torch

Technical Specification

Model	EBT5X
Battery Type	Li-ion
Capacity	19.2Wh, 5200mAh
Input	1A @ 5V DC
Output	5V, 1A (Max)
Dimension (mm)	106.5 x 47 x 25
Weight (g)	133.5

Compatibility

- iPad (all versions): 1A fast charge
- iPhone (4S, 4, 3GS): 1A fast charge

- Android smartphones (all) : upto 1A fast charge (using the included charging cable only)
- Blackberry phones: fast charge (using the included charging cable)
- Kindle Fire: 1A charge
- Samsung Galaxy Tab tablets: 0.5A USB Charge.

Android Devices

Please use the included “charge-only” micro usb cable to charge Android smart phones and tablets at full AC charge. Please note that this cable can not be used for Kindle Fire. Also this cable can only be used for charging and not be used for data synchronization.

Charging your device

1. Please check the remaining charge in EBT5X by pressing (and releasing) the power button.
2. Connect your device to the USB port in EBT5X using an appropriate cable. Use the included Micro USB cable to charge all android and blackberry smartphones for optimized charging.
3. Press the MFB Button to wake up EBT5X if the charging does not start by itself.
4. To stop charging: Simply disconnect the device and the cable.
5. Please note that the EBT5X battery will automatically stop charging when it is discharged.

Charging EBT5X

1. Use the included Micro USB cable to charge EBT5X battery.
2. While the EBT5X battery is being charged, the LED's will flash and light up one after another. All the LED's light up when the battery is completely charged.
3. The battery needs about 6 to 7 hours to get completely charged if connected to 1A port. The charging times may be longer (12 to 13 hours) if connected to other USB chargers or computer USB ports.

Note: Recharge EBT5X once every 3 months if it is not being used.

Checking battery status

To check the current battery status, push the MFB button and check the status of the lit LED's. The table below indicates the capacity remaining in the battery pack.

Power	LED1	LED2	LED3	LED4	LED4
0-20%	●	○	○	○	○
20-40%	●	●	○	○	○
40-60%	●	●	●	○	○
60-80%	●	●	●	●	○
80-100%	●	●	●	●	●

Safety Notice

- Do not expose the product to water, fire and other places with high temperature or Humidity.
- Do not disassemble the battery.
- Do not use the product if there is any electrolytic liquid leakage, overheating, color Change, short-circuit or any other peculiar occurrence.
- Do not use any unauthorized charger to charge EBT5X.
- Do not dispose the battery in trash receptacles and do not attempt to incinerate it.
- Keep away from high voltage devices.

Troubleshooting

Please use these steps to troubleshoot any issue with the EBT5X battery. If you have any other questions or concerns, please contact Kinivo Support at support@kinivo.com

Problem	Solutions
EBT5X cannot be fully charged even after charging for a long time.	<ol style="list-style-type: none">1. The battery pack did not charge completely. Fully Recharge EBT5X battery pack for about 7 hours.2. Check if the charger is working.3. Complete discharge the battery and try charging again.

<p>EBT5X fails to charge the mobile device.</p>	<ol style="list-style-type: none"> 1. The battery pack is discharged. Fully Recharge EBT5X battery pack for about 7 hours. 2. Check whether EBT5X is compatible with the mobile device. 3. Check for any improper connection. Reconnect or replace the connector and cable. 4. The battery may have gone into sleep mode. Press and hold the MFB button for 2-3 seconds to make the battery operational.
<p>Mobile device is not fully charged by EBT5X.</p>	<p>Check if the power is used up. Fully Recharge EBT5X battery pack for about 7 hours.</p>
<p>The LED indicators do not illuminate after pressing the power button.</p>	<ol style="list-style-type: none"> 1. The battery may have gone into sleep mode. Press and hold the MFB button for 2-3 seconds to make the battery operational. 2. The battery pack is discharged. Recharge EBT5X battery pack for about 7 hours.

Warranty

1 Year Limited Hardware Warranty.

Kinivo hereby warrants to the customer of record that this product is in good-working condition and free from defects in material or workmanship under normal use for a duration of 1 year after the date of purchase. The product has been tested to meet the highest quality standards in each testing category. In the unlikely event that the product proves to be defective, Kinivo will repair or

replace the product free of charge. If replacement is required and if Kinivo then no longer carries the same product, then Kinivo reserves the right to substitute the product with a replacement product of like quality and size, suitable for the intended use.

This warranty is limited to repair or replacement of the mentioned product only, is non-transferable and does not extend to any product damaged by misuse, natural disasters or any other circumstances beyond Kinivo's control. The warranty does not cover or provide for the reimbursement or payment of incidental or consequential damage resulting from breach of the limited warranty described above. Except for the limited warranty described above we offer no other warranties expressed or implied, and other than limited warranty expressly contained herein, we hereby disclaim any and all warranties, including without limitation any implied warranties of merchantability, suitability or fitness for a particular purpose.

If your product is not functioning or you have any concerns please contact Kinivo Support before returning the product.

Online Support / Contact Us

Please visit us at support.kinivo.com or www.kinivo.com for support information, downloads and how-to's. You may also reach us via email or live chat (details below).

Kinivo Product Support

Email : support@kinivo.com

Live chat : <http://support.kinivo.com>

KINIVO®

1 year limited
hardware warranty

Kinivo Product Support

Online : <http://support.kinivo.com>

Email : support@kinivo.com

Made in china

